



DIAG. NO.	PART NO.	DESCRIPTION	DIAG. NO.	PART NO.	DESCRIPTION	DIAG. NO.	PART NO.	DESCRIPTION	DIAG. NO.	PART NO.	DESCRIPTION
C1	22-849	TWO GANG VARIABLE	C21	22-851	130MFD ELECTROLYTIC	R15	63-398	330M OHM	16	85-204	DOOR SWITCH
C2	22-182	.00025 MFD	C22	22-851	20MFD	R16	63-713	47M OHM	16	85-203	DOOR SWITCH
C3	22-828	.05 MFD	C23	22-851	10MFD						
C4	22-829	.05MFD	C24	22-470	150 MMFD						
C5	22-594	.15 MFD									
C6	22-863	OSCILLATOR PADDER	R1	63-393	47M OHM	1					
C7	22-868	OSCILLATOR PADDER	R2	63-325	150M OHM	2	56936	WAVEMAGNET ASSEMBLY			
C8	22-848	COMPENSATING COND.	R3	63-1019	60M OHM	3	56937	ANTENNA COIL ASSEMBLY			
C9	22-350	.002 MFD	R4	63-1080	68 OHM WIREWOUND	4	56992	OSCILLATOR COIL ASSEM.			
C10	22-289	50 MMFD	R5	63-150	10M OHM	5	57044	OSC. COUPLER COIL ASSEM.			
C11	22-166	.0001 MFD	R6	63-591	22M OHM	6	85-185	AUTO. TUNING UNIT ASSEM.			
C12	22-196	.01MFD	R7	63-605	1000 OHM	7	85-171	BAND SELECTOR SWITCH			
C13	22-827	.1 MFD	R8	63-271	1MEG OHM	8	85-171	WAVEMAGNET SWITCH			
C14	22-219	.005 MFD	R9	63-655	220 M OHM	9	95-600	TELEVISION SWITCH			
C15	22-854	.0005 MFD	R10	63-1035	VOLUME CONTROL	10	95-612	12 I.F. TRANS			
C16	22-448	.008 MFD	R11	63-296	220 M OHM	11	56994	250 I.F. TRANS			
C17	22-669	.01MFD	R12	63-978	15 MEG OHM	12	100-39	PILOT LIGHT 6.3V .25A			
C18	22-670	.1MFD	R13	63-1083	22 OHM WIREWOUND	13	100-80	PILOT LIGHT 110V 7W.			
C19	22-326	.005 MFD	R14	63-1033	5 SECTON CAND OHM	14	85-192	PHONO SWITCH			
C20	22-658	30MFD ELECTROLYTIC				15	85-191	MOTOR SWITCH			

MODEL SPEAKER
 7S487 49-312 10"
 7S488 49-309 12"
 7S490 49-314 8"

I.F. FREQUENCY 455KC
 7 TUBE SUPERHETERODYNE
 CHASSIS N°5721 3BAND
 VOLTAGE DOUBLER A.C.
 ZENITH RADIO CORPORATION
 CHICAGO, ILL.

MODELS 7S487, 7S488, 7S490 (Chassis No. 5721)