



Sondyna EK 68

| | | |
|------|-------------------------|------------------|
| C 1 | Glimmerkondensator | 50 pf |
| C 2 | " | 32 pf |
| C 3 | Rollblock | 0,05 mf |
| C 4 | " | 2 pf |
| C 5 | Glimmerkondensator | 10 pf |
| C 6 | Rollblock | 0,1 mf |
| C 7 | Glimmerkondensator | 200 pf $\pm 2\%$ |
| C 8 | " | 200 pf $\pm 2\%$ |
| C 9 | " | 200 pf $\pm 2\%$ |
| C 10 | " | 200 pf $\pm 2\%$ |
| C 11 | " | 50 pf |
| C 12 | Keramischer Kondensator | 90 pf |
| C 13 | " | 450 pf |
| C 14 | Rollblock | 5000 pf |
| C 15 | " | 0,1 mf |
| C 16 | Elektrolyt Nieder-Volt | 20 mf 100 V. |
| C 17 | Rollblock | 0,1 mf |
| C 18 | " | 100 pf |
| C 19 | " | 0,05 mf |
| C 20 | " | 0,03 mf |
| C 21 | " | 0,1 mf |
| C 22 | Glimmerkondensator | 1600 pf |
| C 23 | Elektrolyt Nieder-Volt | 50 mf 25 V. |
| C 24 | " | 4 mf 350 V |
| C 25 | " | 4 mf 350 V |
| C 26 | " | 50 mf 25 V. |
| C 27 | " | 4 mf 350 V. |
| C 28 | Elektrolyt-Kondensator | 28 mf 360 V. |
| C 29 | " | 16 mf 360 V. |
| C 30 | Rollblock | 0,1 pf |
| C 31 | " | 5000 pf |
| C 32 | " | 50 pf |

| | | |
|------|------------|------------------|
| W 1 | Widerstand | 160 ohm |
| W 2 | " | 1 m. ohm |
| W 3 | " | 300 ohm |
| W 4 | " | 50 k. ohm |
| W 5 | " | 2,5 k. ohm |
| W 6 | " | 300 ohm |
| W 7 | " | 50 k. ohm 1 Watt |
| W 8 | " | 8 k. ohm 2 Watt |
| W 9 | " | 25 k. ohm 5 Watt |
| W 10 | " | 1 m. ohm |
| W 11 | " | 1 m. ohm |
| W 12 | " | 100 k. ohm |
| W 13 | " | 0,5 m. ohm |
| W 14 | " | 100 k. ohm |
| W 15 | " | 1 m. ohm |
| W 16 | " | 1 m. ohm |
| W 17 | " | 2 m. ohm |
| W 18 | " | 25 ohm |
| W 19 | " | 3200 ohm |
| W 20 | " | 200 k. ohm |
| W 21 | " | 1 k. ohm |
| W 22 | " | 100 k. ohm |
| W 23 | " | 40 k. ohm |
| W 24 | " | 0,5 m. ohm |
| W 25 | " | 160 ohm 1 Watt |
| W 26 | " | 300 ohm |

Sondyna A.G.
Zürich

EK 68

Zwischenfrequenz = 465 kHz

Sicherungen: 220 - 250 Volt = 600 M. Amp.
110 - 145 Volt = 1000 M. Amp.

Skatallämpchen: 6,5 Volt, 0,2 Amp.