



Sondyna Piccolo 3

Widerstände:

W 1	30	Ohm	1/4 Watt
W 2	80	Ohm	1/2 Watt
W 3	100	Ohm	1/2 Watt
W 4	2,5 k.	Ohm	1/4 Watt
W 5	2,5 k.	Ohm	1/4 Watt
W 6	2,5 k.	Ohm	1/4 Watt
W 7	30 k.	Ohm	1 Watt
W 8	40 k.	Ohm	1/2 Watt
W 9	50 k.	Ohm	1/2 Watt
W 10	50 k.	Ohm	1/4 Watt
W 11	100 k.	Ohm	1/2 Watt
W 12	100 k.	Ohm	1/2 Watt
W 13	100 k.	Ohm	1/4 Watt
W 14	100 k.	Ohm	1/4 Watt
W 15	0,5 m.	Ohm	1/4 Watt
W 16	0,5 m.	Ohm	1/4 Watt
W 17	1 m.	Ohm	1/4 Watt
W 18	1 m.	Ohm	1/4 Watt
W 19	1 m.	Ohm	1/4 Watt
W 20	2 m.	Ohm	1/4 Watt
W 21	2 m.	Ohm	1/4 Watt

Sondyna A.G.
Zürich

Kondensatoren:

C 1	50	pF	Glimmer	
C 2	50	pF	"	
C 3	50	pF	"	
C 4	50	pF	"	
C 5	200	pF	"	} ± 2,5%
C 6	200	pF	"	
C 7	200	pF	"	
C 8	200	pF	"	
C 9	450	pF	"	
C 10	390	pF	Rollblock	
C 11	5000	pF	"	
C 12	0,01	mF	"	
C 13	0,09	mF	"	
C 14	0,05	mF	"	
C 15	0,05	mF	"	
C 16	0,05	mF	"	
C 17	0,05	mF	"	
C 18	0,05	mF	"	
C 19	0,05	mF	"	
C 20	0,3	mF	"	
C 21	0,3	mF	"	
C 22	4	mF	Elektrolyt	350—400 V.
C 23	8	mF	"	450—525 V.
C 24	8	mF	"	450—525 V.

Zwischenfrequenz: = 472 kHz

Sicherung: = 500 M. Amp.

Skalalämpchen: = 6,3 Volt, 0,3 Amp.

Röhren: ECH 3, EBF 2, ECL 11, AZ 1