



Mediator

Widerstand	Kodenummer	Preis
2000 ohm	28.802.000	
50 ohm	28.773.370	
0,1 Mohm	28.773.900	
50000 ohm	28.773.870	
10000 ohm	28.803.080	
250 ohm	28.773.640	
0,3 Mohm	28.773.960	
10000 ohm	28.814.550	
2000 ohm	28.770.570	
10000 ohm	28.773.730	
10000 ohm	28.773.760	

Widerstand	Kodenummer	Preis
1,6 Mohm	28.770.570	
25000 ohm	28.773.840	
0,5 Mohm	28.773.970	
0,2 Mohm	28.773.930	
0,8 Mohm	28.773.990	
1000 ohm	28.773.700	
100 ohm	28.770.170	
0,16 Mohm	28.773.920	
50000 ohm	28.812.500	
320 ohm	28.773.650	
100 ohm	28.773.600	
0,1 Mohm	28.773.990	

* Ausführung 29.

RÖHREN

1.1	1.2	1.3	1.4	1.5	1.6
AK2	AK3	AKC1	AK4	AZ1	8012-07

Mediator 43

SPULEN

Widerstand	Kodenummer	Preis
—	28.534.580	
100 ohm	28.534.590	
—	28.534.930	
130 ohm	28.587.880	
25 ohm	—	
110 ohm	—	
4 ohm	28.571.590	
40 ohm	—	
4 ohm	—	
40 ohm	—	
4 ohm	—	
40 ohm	—	
2,5 ohm	28.571.790	
—	—	
9 ohm	—	
3,5 ohm	—	
30 ohm	28.571.800	
7 ohm	28.572.270	
—	—	
30 ohm	—	
130 ohm	28.571.770	
130 ohm	—	
130 ohm	28.572.390	
35 ohm	—	
90 ohm	—	
690 ohm	28.533.720	
—	—	
5 ohm	28.220.510	
—	—	
—	28.587.690	

1) Ausführung 29; 2) Ausf. 14; 3) Ausf. 13.

SPANNUNGEN UND STRÖME

	L1	L2	L3	L4	L5	
Va	230	230	65	250	270 ~	V=
Vg	2,8	2,3	2,3	5	—	V=
Vg2	87	87	—	230	—	V=
Vg3-5	87	—	—	—	—	V=
Ia	1,8	6,8	0,56	37	—	mA=
Ig2	2	2,6	—	4,7	—	mA=
Ig3-5	4,2	—	—	—	—	mA=

Spannung über L1: 275 V
Spannung über L2: 230 V

Spannung Kathode L3-Chassis: 16 V

Achtung: Folgende Widerstände sind geändert:

ALT	NEU
R9	0,5 M.ohm
R21	0,16 M.ohm

⚠ FÄLLT WEG BEI 461A-04 (OHNE KURZWELLEN)