



SPEAKER	MODEL
49-238-5 IN	5-R-312
49-238-5 *	5-R-316
49-238-5 *	5-R-317
49-238-5 *	5-R-337
49-238-5 *	5-R-303

DIAG. NO.	PART NO.	DESCRIPTION	DIAG. NO.	PART NO.	DESCRIPTION	DIAG. NO.	PART NO.	DESCRIPTION
C-1	22-695	THD GANG VAR COND.	R-1	63-597	470 M OHM	4		
C-2	22-289	50 MMFD.	R-2	63-593	47 M OHM	5	95-515	1ST I.F. TRANS.
C-3	22-162	.0001 MFD.	R-3	63-208	12 M OHM	6	95-520	2ND I.F. TRANS.
C-4	22-250	.05 MFD.	R-4	63-271	1 MEG OHM	7	95-521	POWER TRANS. (117V. 50-60~)
C-5	22-519	TRIMMER COND.	R-5	63-296	220 M OHM	8	95-523	POWER TRANS. 25~
C-6	22-729	COMPENSATING COND.	R-6	63-658	390 M OHM	9	100-36	PILOT LIGHT .25A 6.3V
C-7	22-182	.00025 MFD.	R-7	63-280	100 M OHM	10		SPEAKER TRANS.
C-8	22-212	.05 MFD.	R-8	63-583	80 OHM WIRE WOUND	A		1ST I.F. TRANS. PRI.
C-9	22-196	.01 MFD.	R-9	63-686	150 OHM WIRE WOUND	B		1ST I.F. TRANS. SEC.
C-10	22-147	.0005 MFD.	R-10	63-955	220 M OHM VOL. CONT.	C		2ND I.F. TRANS. PRI.
C-12	22-691	8 MFD. ELECTROLYTIC 450V	1	5-5000	ANTENNA COIL ASSEM.	D		2ND I.F. TRANS. SEC.
C-13	22-692	8 MFD. ELECTROLYTIC 350V	2	5-6039	OSC. COIL ASSEM.	F		BROADCAST OSC. (100KANG)
			3	20-187	COMPENSATING COIL	G		ANTENNA BRD CRST (100KANG)

I.F. FREQUENCY 455 K.C.
5 TUBE SUPERHETERODYNE
CHASSIS NO 5528 A.C.
ZENITH RADIO CORPORATION