



DIAG. NO.	PART NUMBER	DESCRIPTION	DIAG. NO.	PART NUMBER	DESCRIPTION
R1	63-278	99 M OHMS	C9	22-408	2-35 MMFD. PADDER
R2	63-361	5 M	C10	22-82	.001 MFD.
R3	63-362	400	C11	22-212	.05
R4	63-280	4.9 M	C12	22-182	.00025
R5	63-353	1.9 M	C13	22-224	.1
R6	63-293	990 M	C14	22-225	.5
R7	63-290	260 M	C15	22-437	.01
R8	63-258	490 M	C16	22-228	.5
R9	63-272	4 M	C17	22-251	.5
R10	63-238	1 M	C18	22-432	.8
R11	63-260	100 M	C19		
R12	63-477	100 FLEXIBLE WIRE WOUND	C20	22-409	456 MMF. VAR. COND.
R13	63-394	200 OHMS	1	5-3697	ANT. COIL ASSEM.
R14	63-456	200 M VOL. CONTROL & SWITCH	2	5-3698	DET. COIL ASSEM.
R15	63-458	50 M TONE CONTROL	3	5-3699	OSC. COIL ASSEM.
C1	22-243	.01 MFD.	4	20-82	ANT. CHOKE
C2	22-410	.003	5	20-88	R.F. CHOKE
C3	22-250	.05	6	20-119	R.F. PLATE CHOKE
C4	22-289	50 MMFD.	7	5-2778	R.F. CHOKE
C5	22-188	.02 MFD.	8	85-78	BAND SELECTOR SWITCH
C6	22-411	.0023	9	95-291	1ST. I.F. TRANS.
C7	22-345	.0011	10	95-292	2ND. I.F. TRANS.
C8	22-205	200-350 MMFD. PADDER	11	95-298	POWER CHOKE
			12	95-305	RECTIFIER TRANS.
			13	95-311	AUDIO TRANS.
			14	49-132	8" MAG. SPEAKER MOD. 6V27
			15	49-134	12" DYN. MOD. 6V62

# ZENITH

3 BAND { 550 KC. - 1780 KC.  
2100 KC. - 6800 KC.  
7000 KC. - 23000 KC.

I.F. FREQUENCY 456 KC.  
6 TUBE BATTERY SUPERHETERODYNE  
CHASSIS NO 5621

MODELS - 6V27, 6V62

ZENITH RADIO CORP.  
CHICAGO, ILL.

16 190-5 VIBRATOR