		Description.	Part No.
ELECTRICAL COMPONENTS OF UNIT— *continued.*			
		Insulating bush	7632
		Insulating washer	776
CK 1	...	H.F. choke	1527-C
		Screw securing CK 1	4087
CK 2	...	L.F. choke	4750-C
		Shorting link for CK 2	1518
		Screw securing shorting link ...	4087
T 1	...	Intervalve transformer	4518-F
		Screws securing T 1 & CK 2 ...	2462
		Shakeproof washer	3166
T 2	...	Mains transformer with pillars ...	7571-A
		Voltage adjusting screw	2458
		Nut securing T 2 to chassis ...	7657
VR 1	...	Volume control, 10,000 ohm ...	6000-B
VR 2	...	100,000 ohm ...	
		Large nut securing VR 1 and VR 2...	4400
VR 3	...	Hum adjustment potentiometer ...	10201-C
C 1	...	Fixed condenser, 5,000 mmfd. (·005)	7974-A
C 3	...	,, ,, 300 mmfd. (·0003)	4774-A
C 4	...	,, ,, 50 mmfd. (·00005)	7607-A
C 5	...	,, ,, 2,000 mmfd. (·002)	1872-A
C 6	...	,, ,, 300 mmfd. (·0003)	4774-A
		Screw securing condenser block ...	4087
		Nut for above screw	5612
		Shakeproof washer	3165
C 13	...	Fixed condenser, 2,000 mmfd. (·002)	1872-A
C 15	...	Fixed condenser, 8·0 mfd. electrolytic	5662-A
C 16	...	,, ,, 8·0 mfd. electrolytic	5662-A
		Screw securing C 15, C 16, C 19 ...	2701
		Nut for above screw	5603
C 2	...	Fixed Condenser, 1·0 mfd. ...	7581-A
C 7	...	,, ,, 1·0 ,, ...	
C 8	...	,, ,, ·5 ,, ...	
C 9	...	,, ,, 1·0 ,, ...	
C 10	...	,, ,, ·1 ,, ...	
C 11	...	,, ,, ·5 ,, ...	
C 12	...	,, ,, ·1 ,, ...	
C 14	...	,, ,, ·5 ,, ...	
C 17	...	,, ,, 1·0 ,, ...	
C 18	...	,, ,, 4·0 ,, ...	
C 19	...	Fixed condenser, 8·0 mfd., electrolytic	5662-A
R 1	...	Fixed resistance, 5,000 ohm ...	5787-F
R 2	...	,, ,, 25,000 ,, ...	5787-H
R 3	...	,, ,, 900 ,, ...	5787-J
R 4	...	,, ,, 2,000 ,, ...	5787-A
R 5	...	,, ,, 900 ,, ...	5787-J
R 6	...	,, ,, 25,000 ,, ...	5786-C
R 7	...	,, ,, 150,000 ,, ...	8762-A
R 8	...	,, ,, 100,000 ,, ...	5787-Q
R 9	...	,, ,, 6,000 ,, ...	5786-F
R 10	...	,, ,, 1,000 ,, ...	5787-K
R 11	...	,, ,, 5,000 ,, ...	5787-F
R 12	...	,, ,, 50,000 ,, ...	5787-P
R 13	...	,, ,, 50,000 ,, ...	5787-P
R 14	...	,, ,, 2,000 ,, ...	5786-E
R 15	...	,, ,, 2,000 ,, ...	5786-E
R 16	...	,, ,, 10,000 ,, ...	10187-A
R 17	...	,, ,, 7,000 ,, ...	5787-M
S 10	...	Local distant switch	740-B
S 11	...	Change over switch (for Components, see under Mechanical Components)	739-B

PLUGS, SOCKETS, BUSHES, ETC., ON RADIO UNIT—

Mains plug pin	... ...		4877
Insulating block plain	... ...		4863