

# ANALYSEUR de SORTIE Type 750.

## Tableau de correspondances.

C = CONDENSATEURS					K = GALETIES de CONTACTEURS				
N°	Valeur	Genre	Tolér.	Planchens	N°	Genre	Planchens		
C1	1 µF	Papier	1500v.	8, 9, 14,	R12	1 Ω	Bobinée ±1%	8, 9	
C2	8 µF	Chim.	450v.	8, 9, 14,	R12b	0,5 Ω	" "	8, 9	
C3	22 µF	Gratt.		5, 7,	R13	3000 Ω	" "	8, 9	
C4	5 µF	"		5, 7,	R14	2000 Ω	" "	8, 9	
C5	0,1 µF	Papier	1500v.	5, 7,	R15	2000 Ω	" "	8, 9	
C6	8 µF	Chim.	450v.	5, 7,	R16	14,00 Ω	" "	8, 9	
C7	25.000 µF	Papier		5, 7,	R17	11,00 Ω	" "	8, 9	
C8	"	"		5, 7,	R18	1.000 Ω	" "	8, 9	
C9	"	"		5, 7,	R19	700 Ω	" "	8, 9	
C10	900 µF	Mica		5, 7,	R20	600 Ω	" "	8, 9	
C11	0,1 µF	Papier		5, 6,	R21	400 Ω	" "	8, 9	
C12	30.000 µF	"	±2%	10, 11,	R22	300 Ω	" "	8, 9	
C13	16.000 µF	"	±2%	10, 11,	R23	1.000 Ω	" "	8, 9	
C14	25.000 µF	"	±2%	10, 11,	R23b	500 Ω	" "	8, 9	
C15	0,1 µF	"	±2%	10, 11,	R24	1.500 Ω	" "	8, 9	
C16	25 µF	Chim.	23v.	5, 6,	R25	1.450 Ω	" "	8, 9	
C17	8 µF	"	450v.	5, 6,	R26	1.570 Ω	" "	8, 9	
C18	0,1 µF	Papier		5, 6,	R27	1.270 Ω	" "	8, 9	
C19	0,5 µF	"		5, 6,	R28	1.290 Ω	" "	8, 9	
C20	8 µF	Chim.	450v.	3, 4,	R29	990 Ω	" "	8, 9	
C21	0,5 µF	Papier	1500v.	3, 4,	R30	900 Ω	" "	8, 9	
C22	8 µF	Chim.	450v.	3, 4,	R31	910 Ω	" "	8, 9	
C23	250 µF	Mica		3, 4,	R32	670 Ω	" "	8, 9	
C24	4.000 µF	Papier	2%	12, 13	R33	690 Ω	" "	8, 9	
C25	1.700 µF	"	2%	12, 13	R34	5.460 Ω	" "	8, 9	
C26	3.100 µF	"	2%	12, 13	R35	342 KΩ	1w.	5, 7	
C27	15.000 µF	"	2%	12, 13	R36	108 KΩ	"	5, 7	
C28	9.000 µF	"	2%	12, 13	R37	50 KΩ	"	5, 7	
C29	4.000 µF	"	2%	12, 13	R38	1,08 MΩ	"	5, 7	
C30	7.000 µF	"	2%	12, 13	R39	"	"	5, 7	
C31	25.000 µF	"	2%	12, 13	R40	0,5 MΩ	"	5, 7	
C32	15.000 µF	"	2%	12, 13	R41	0,119 MΩ	"	5, 7	
C33	8.000 µF	"	2%	12, 13	R42	1,53 MΩ	"	5, 7	
C34	12.500 µF	"	2%	12, 13	R43	34,2 KΩ	"	5, 7	
C35	50.000 µF	"	2%	12, 13	R44	10,8 KΩ	"	5, 7	
C36	90.000 µF	"	2%	12, 13	R45	3420 Ω	"	5, 7	
C37	39.000 µF	"	2%	12, 13	R46	108v	bobinée ±1%	5, 7	
C38	70.000 µF	"	2%	12, 13	R47	342 Ω	" "	5, 7	
C39	0,25 µF	"	2%	12, 13	R48	158 Ω	" "	5, 7	
C40	0,25 µF	"	2%	12, 13	R49	100 Ω	0,5w.	5, 7	
C41	0,11 µF	"	2%	12, 13	R50	1 KΩ	2w.	5, 7	
C42	0,2 µF	"	2%	12, 13	R51	52,5 Ω	Bobinée ±1%	5, 7, 14, 15, 16	
C43	0,82 µF	"	2%	12, 13	R52	0,1 MΩ	0,5w.	5, 7	
					R53	20 KΩ	1	5, 7, 16	
					R54	10 KΩ	1	5, 7, 16	
					R55	0,1 MΩ	0,5w.	5, 7	
					R56	"	"	5, 7	
					R57	2000 Ω	"	±1% 5, 7, 15, 16	
					R58	8000 Ω	"	±1% 5, 7, 15, 16	
					R59	1 MΩ	1w.	5, 6	
					R60	10 KΩ	1	5, 7	
					R61	2 KΩ	0,5	5, 6	
					R62	0,25	1	5, 6	
					R63	50 KΩ	0,5	5, 6	
					R64	1 MΩ	1	5, 6	
					R65	1 KΩ	0,5	5, 6	
					R66	100 KΩ	2	5, 6	
					R67	0,119 MΩ	1	5, 6	
					R68	0,1 MΩ	2	5, 6	
					R69	500 Ω	Bob. 5w.	3, 4	
					R70	1 MΩ	1w.	3, 4	
					R71	200 Ω	1w.	3, 4	

  

L = SELFS				
N°	Nom	Planchens		
L1	Self 1,56 Hy	10, 11,		
L2	Self 1,24 Hy	10, 11,		
L3	Transfo. d'alimentation	3, 4,		
L4	Self de filtrage n° 116	3, 4,		
L5	Self 0,20 Hy	12, 13		
L6	" 0,16 "	12, 13		
L7	" 0,45 "	12, 13		
L8	" 0,35 "	12, 13		
L9	" 0,78 "	12, 13		
L10	" 0,62 "	12, 13		
L11	" 4,5 "	12, 13		
L12	" 3,4 "	12, 13		
L13	" 12,5 "	12, 13		
L14	" 9,9 "	12, 13		

  

P = POTENTIOMETRES				
N°	Valeur	Genre	Planchens	
P1	1.000 Ω	Bobiné	5, 7, 14, 15, 16,	
P2	10.000 Ω	Bobiné „Alter“	5, 7, 16,	
P3	1.000 Ω	" "	5, 6,	
P4	1.000 Ω	Bobiné „Loto“	5, 6,	
P5	10.000 Ω	Graphite „Alter“	5, 6,	
P6	400 Ω	Bobiné „Loto“	5, 6,	
P7	"	"	3, 4	

  

G = GALVANOMETRES				
N°	Valeur	Planchens		
G1	100 µA	5, 6,		

  

R = RESISTANCES				
N°	Valeur	Watt.	Tolér.	Planchens
R1	0,5 MΩ	1w.		8, 9, 14
R2	3 Ω	Bobinée ±1%		8, 9
R3	2 Ω	"		8, 9
R4	2 Ω	"		8, 9
R5	1,4 Ω	"		8, 9
R6	1,1 Ω	"		8, 9
R7	1 Ω	"		8, 9
R8	0,7 Ω	"		8, 9
R9	0,6 Ω	"		8, 9
R10	0,4 Ω	"		8, 9
R11	0,3 Ω	"		8, 9

  

V = LAMPES				
N°	Type	Planchens		
V1	E L 3	5, 7, 14, 15, 16		
V2	6 F 5	5, 6,		
V3	6 C 5	5, 6,		
V4	6 H 6	5, 6,		
V5	E L 3	3, 4,		
V6	5 Y 3 G B	3, 4,		
V7	Témoin 6,3 v. 0,3 A.	3, 4,		