

(L' = L'')

T.			U_f	I_f	U_a	U_{g2}	U_{g1}	I_a	I_{g2}	S	R_i	R_o	P_o
			V	A	V	V	V	mA	mA	mA/V	kΩ	kΩ	W
ELL 1	eur	1	6,3	0,45	250	250	-20	15	2,5	1,7	110		
12 L 8-GT	amer	2	12,6	0,15	110	110	- 5,5	6,1	1,3	1,68		14	0,3
					180	180	- 9	13	2,8	2,15	160	10	1
					180	180	maximum $(P_a=2,5\text{ W}; P_{g2}=1\text{ W}; U_{f/k}=100\text{ V})$						
5656	Ray	3	6,3	0,4	150	120	- 2	15	2,7	5,8	60		

Equivalents

CK 5656	Ray = 5656
1644	amer = 12 L 8-GT

