

T.			U_f		I_f	U_a		U_{g2}		U_{g1}		I_a	I_{g2}	S	R_i	R_o	P_o	P_a
			V	A		V	V	V	V	V	mA				kΩ	kΩ	W	W
B 543	Phl	1/2/3	5	0,1	200	150	—15	12	2,5	1,3	45	10	1,15	3				
C 643	Phl	1	6	0,25	300	200	—20	21	5,5	1,5	45	15	2,8	8				

Equivalents

B 543 S	Phl = B 543	M 1006	Rec = B 543	Tu = C 643
DP 1	Oxt = B 543	P 520	Tri = B 543	MOG = C 643
E 615	Tri = C 643	PD 5	Tri = B 543	Cos = C 643
L 103	Sat = B 543	PM 25	Mul = B 543	Tlf = B 543
L 506	Mrh = B 543	PM 25 DC	Mul = B 543	Vat = B 543
L 510 D	Val = B 543	PM 26	Mul = C 643	Mul = B 543
LL 610	Sat = B 543	PP 610	Tu = B 543	Cas = B 543

