
MODEL "Q"  
SHORT WAVE-BROADCAST RECEIVER

DESIGNED BY ARNOLD  
CHECKED BY  
SILVER-MARSHALL  
2-23-32  
3-10-32  
4-12-32  
DWS.No.155-4

NOTE -  
ALL VOLTAGES TAKEN  
FROM GROUND.

Model Q (S.W. & Broadcast) (1932)



- L1 - 197 Broadcast Antenna Coil (550-1500 kc.)
- L2 - 202 Short Wave antenna Coil (1.56-3.46 megacycles)
- L3 - 201 Short Wave Antenna Coil (3.51-5.36 megacycles)
- L4 - 200 Short Wave Antenna Coil (5.54-10.29 megacycles)
- L5 - 199 Short Wave Antenna Coil (9.6-18.15 megacycles)
- L6 - 198 Oscillator Coil
- L8 - 283 R.F. Choke

M - Tuning Meter - 15 m.a. 13923

- C1-C2 365 mmfd
- C3 25 mmfd
- C4 200 mmfd
- C5 4. mfd
- C6 0.1 mfd
- C7 0.1 mfd
- C8 0.1 mfd
- C9 0.1 mfd
- C10 0.5 mfd
- C11 .001 mfd
- C12 .001 mfd
- C13 .025 mfd
- C14 .025 mfd
- C15 .03 mfd
- C16 .00015 mfd
- C17 Osc Fr.
- C18 0.1 mfd
- C19 0.1 mfd
- C20 0.15 mfd
- C21 .0005 mfd
- C22 0.5 mfd
- C23 See diagram
- C24 12 mfd
- C25 8 mfd
- C26 4 mfd
- R9 1. meg
- R10 1. meg
- R11 12000 ohms
- R12 9000 ohms
- R13 8250 ohms
- R14 6500 ohms
- R15 30000 ohms
- R16 400 ohms
- R17 400 ohms
- R18 30000 ohms
- R19 3500 ohms
- R20 60000 ohms
- R21 60000 ohms
- R22 220 ohms
- P1 10000 ohms
- P2 25000 ohms
- R8 1. meg