


RCA Victor

MODELS 96X-1, -2, -3, -4 and -11, -12, -13, -14

Chassis No. RC-400 and RC-400A

Six-Tube, Two-Band, A-C—D-C, Superheterodyne Receivers



On some models 25L6 plate condenser is .025 mfd.


Alignment Procedure

Output Meter Alignment.—Connect the meter across the voice coil, and turn the receiver volume control to maximum.

Test-Oscillator.—Connect the low side of the test-oscillator to the receiver chassis, through a .01 mfd. capacitor, and keep the output as low as possible.

Dial Setting.—To set dial indicator drum, turn tuning condensers fully clockwise and then counter-clockwise.

Push-button Adjustments.—Remove bakelite button and loosen screw two turns with a screwdriver or coin. Tune in the desired station by means of the right-hand control knob. Press push lever down as far as it will go and tighten screw. Release lever and put on push-button.



Steps	Connect the high side of test-oscillator to—	Tune test-osc. to—	Turn radio dial to—	Adjust the following for max. peak output—
1	Tuning condenser stator (osc.) in series with .01 mfd.†	455 kc	Quiet point between 550-750 kc	C1, C2, C3, C4 (1st and 2nd I-F transformer)
2	Antenna lead (yellow) in series with 400 ohms	19.25 mc	Full clockwise (out of mesh) "C" band	C5* (osc.)
3	Same as step 2	15.0 mc	15.0 mc Test oscillator signal	C6** (ant.) See Note No. 1
4	Antenna lead in series with 200 mmf condenser	1,745 kc	Full clockwise (out of mesh) "A" band	C7 (osc.)

* Use minimum capacity peak if two peaks can be obtained.

** Rock gang slightly and check to determine that C5 has been adjusted to the correct peak by tuning to approximately 14.09 mc, where a weaker signal should be received.

† Make test oscillator connection to lug on tuning condenser stator (oscillator section) in series with .01 mfd. condenser.

Note No. 1.—Accurately tune receiver to the 15.0 mc test oscillator signal. This signal will appear twice (14.09 and 15.0 mc) as dial is turned. Use the higher frequency setting of the tuning condensers (gang furthest out of mesh).

Note No. 2.—Oscillator tracks 455 kc above signal on all bands.