




Note: On some receivers the following circuit modifications are in effect:

1. R11 is 4,700 ohms, and C18 is .05 mfd.
2. C1 is 470 mmfd.
3. There are three types of 2nd I-F transformers in use.
 - a. The first type (Stock No. 14308) has C23 and R5 mounted inside the case, and is connected exactly as shown above.
 - b. In the second type R5 is omitted and the lead from S4 connects to C instead of E. E is not used.
 - c. In the third type R5 is omitted and C23 is connected externally from C to ground. E is not used. The lead from the diode plate connects to A instead of B.



MODEL R-60

