



# RCA VICTOR

## 8-X-5 SERIES, 8-X-6 SERIES MODEL 8-X-51

Chassis No. RC-1170, RC-1178

8-C-5 Series and Model 8-C-51, using Chassis RC-1179, are like RC-1170, and 8-C-6 Series, Chassis RC-1179A, are like RC-1178, except of addition of timer with switch.

### Alignment Procedure

Step	Connect the high side of test-oscillator to—	Tune test-osc. to—	Turn radio dial to—	Adjust the following for max. output
1	12BA6 I-F grid through .01 mfd. capacitor	455 kc	Quiet-point 1,600 kc end of dial	T2 (top) 2nd I-F trans.
2	Stator of C1-B through .01 mfd.			T1 (top and bottom) 1st I-F trans.
3		1,620 kc	Gang fully open	osc. trimmer C1-A
4	Short wire placed near loop to radiate signal	1,400 kc	1,400 kc signal	ant. trimmer C1-B
5		600 kc	600 kc signal	osc. coil T-4 (rock gang)
6	Repeat steps 3, 4, and 5			

