





E 4612

 $ZF = 470 \text{ kHz}$ 

Lautsprecher

Kondensatoren

C 1	500 pf	10	%	Gl.
2	100 pf	10	%	Gl.
3	50 pf	5	%	Gl.
4	5-40 pf			Tr.
5	5-30 pf			Tr.
6	5-30 pf			Tr.
7	6000 pf	10	%	Gl.
8	1.Segm.			Drehko.
9	100 pf	10	%	Gl.
10	0,075 mf	1500	V.	P.
11	200 pf	1	%	Gl.
12	50 pf	10	%	Gl.
13	2.Segm.			Drehko.
14	100 pf	10	%	Gl.
15	187 pf	1	%	Gl.
16	530 pf	1	%	Gl.
17	5-40 pf			Tr.
18	5-30 pf			Tr.
19	5-30 pf			Tr.
20	30 pf	10	%	Gl.
21	20 pf	10	%	Gl.
22	0,05 mf	1500	V.	P.
23	200 pf	1	%	Gl.
24	0,05 mf	500	V.	P.
25	200 pf	1	%	Gl.
26	100 pf	10	%	Gl.
27	100 pf	10	%	Gl.
28	0,05 mf	500	V.	P.
29	10 mf	12/15	V.	Elko.
30	3000 pf	1500	V.	P.
31	200 pf	1	%	Gl.
32	4 mf	420/535	V.	Elko.
33	0,02 mf	1500	V.	P.
34	50 mf	20/25	V.	Elko.
35	3000 pf	2500	V.	P.
36	50 pf	10	%	Gl.
37	2 x 30 mf	450/525	V.	Elko.
39	10 pf	10	%	Gl.

Widerstände

R 1	1	mOhm	1/2 W.
2	16	k	3 W.
3	750	"	1 W.
4	30	"	1/2 W.
5	51	K	1/2 W.
6	20	k	2 W.
7	0,1	m	1/2 W.
8	0,39	m	1/2 W.
9	0,5	m	1/4 W. log.
10	10	k	1/2 W.
11	0,5	m	1/4 W. lin.
12	0,1	m	1 W.
13	10	k	1/2 W.
14	1	k	1/2 W.
15	0,51	m	1/2 W.
16	130	"	1 W.
19	1	m	1/2 W.
20	1	m	1/4 W.
21	1	k	12 W.
22	30	"	1/2 W.
23	0,1	m	1/2 W.
24	60	k	2 W.
25	0,1	m	1/2 W.
26	51	k	1/2 W.
30	10/14	k	2 W.

Sicherungen

5 x 25 mm

Prim.

1000 mA

125 mA

Sondyna A.G.
Zürich