



Stückliste

zu Schaltbild A.W.S. 501/3, 4, 5, 6

Siemens Albis 434, D, G, GS, GSD

Pos. 434	Pos. 434 D	Pos. 434 G	Pos. 434 GS	Pos. 434 GSD	Gegenstand	Daten	Pos. 434	Pos. 434 D	Pos. 434 G	Pos. 434 GS	Pos. 434 GSD	Gegenstand	Daten
7	7	7	7	7	Sperrkreisspule		64	64	64	64	64	Widerstand	100 Ohm
8	8	8	8	8	Ankopplungsspule kurz		65	65	65	65	65	"	50 Ohm
9	9	9	9	9	" mittel		66	66	66	66	66	"	40 kOhm
10	10	10	10	10	" lang		67	67	67	67	67	"	2 MOhm
11	11	11	11	11	Vorkreisspule kurz		68	68	68	68	68	"	20 kOhm
12	12	12	12	12	" mittel		69	69	69	69	69	"	80 kOhm
13	13	13	13	13	" lang		70	70	70	70	70	"	1 MOhm
14	14	14	14	14	Oszillatorkreis spule kurz		71	71	71	71	71	"	200 kOhm
15	15	15	15	15	" mittel		72	72	72	72	72	"	100 kOhm
16	16	16	16	16	" lang		73	73	73	73	73	Lautstärkeregl. Widerstand	1 kOhm
17	17	17	17	17	Rückkopplungsspule kurz		74	74	74	74	74	"	500 kOhm
18	18	18	18	18	Bandfilter spule		75	75	75	75	75	"	10 kOhm
19	19	19	19	19	"		76	76	76	76	76	"	150 kOhm
20	20	20	20	20	"		77	77	77	77	77	"	5 kOhm
21	21	21	21	21	"		78	78	78	78	78	"	1,5 kOhm
.	Vorkreis kpl., bestehend aus den Pos. 8, 9, 10, 11, 12, 13, 25, 26, 27, 28.		79	79	79	79	79	"	100 kOhm
.	Oszillatorkreis kpl., bestehend aus den Pos. 14, 15, 16, 17, 31, 32, 34, 35.		80	80	80	80	80	"	1 kOhm
.	Spulensatz kpl., bestehend aus Vorkreis, Oszillatorkreis, sowie den Schalterplatten mit den Kontakten A... und B...		81	81	81	81	81	"	500 kOhm
.	1. ZF-Bandfilter kpl., enthaltend die Pos. 18, 19, 37, 38.		82	82	82	82	82	"	150 kOhm
.	2. ZF-Bandfilter kpl., enthaltend die Pos. 20, 21, 39, 40.		83	83	83	83	83	"	1,5 kOhm
.			84	84	84	84	84	"	1,5 kOhm
.			85	85	85	85	85	"	1 MOhm
.			86	86	86	86	86	"	30 Ohm
.			87	87	87	87	87	"	50 Ohm
.			88	88	88	88	88	"	1,5 MOhm
.			89	89	89	89	89	"	30 kOhm
22	22	22	22	22	Kondensator	500 pF	90	90	90	90	90	adwangsübertrager	
23	23	23	23	23	Antennenkondensator	500 pF)	91	91	91	91	91	Schwingenspule	
24	24	24	24	24	"	100 pF)	92	92	92	92	92	Polispuie	
25	25	25	25	25	Kondensator	10 pF	93	93	93	93	93	Kompensationspule	
26	26	26	26	26	Vorkreisstromer mittel		94	94	94	94	94	Netztransformat.	
27	27	27	27	27	Kondensator	22 pF	95	95	95	95	95	Thermosicherung	
28	28	28	28	28	"	0,1 pF	96	96	96	96	96	Netzschalter	
29	29	29	29	29	Zweigangdrenkondensator		97	97	97	97	97	Skalenteleuchtungs Lampe	6,3 V; 0,32 A.
30	30	30	30	30	Kondensator	50 pF	98	98	98	98	98	"	6,3 V; 0,32 A.
31	31	31	31	31	Oszillatorbrunmer mittel		99	99	99	99	99	Kondensator	0,3 pF
32	32	32	32	32	" lang		-	102	-	-	102	"	10000 pF
34	34	34	34	34	Verkürzungskondensator mittel	400 pF	-	103	-	-	103	Widerstand	15 kOhm
35	35	35	35	35	" lang	206 pF	-	104	-	-	104	"	5 kOhm
36	36	36	36	36	Kondensator	500 pF	-	105	-	-	105	"	1 kOhm
37	37	37	37	37	"	120 pF	-	106	-	-	106	"	1 MOhm
38	38	38	38	38	"	120 pF	-	107	-	-	107	Lautstärkeregl.	
39	39	39	39	39	"	120 pF	-	108	-	-	108	Drabtfunkübertrager	
40	40	40	40	40	"	120 pF	-	109	-	-	109	Netztransformat.	
41	41	41	41	41	"	0,1 pF	-	110	-	-	110	Netzschalter	
42	42	42	42	42	"	100 pF	-	111	-	-	111	Feinrechtsicherung	700 mA
43	43	43	43	43	"	100 pF	-	112	-	-	112	"	700 mA
44	44	44	44	44	"	10000 pF	-	113	-	-	113	Trennkontakt	
45	45	45	45	45	"	0,1 pF	-	114	-	-	114	Impulskontakt	
46	46	46	46	46	Elektrolytkondensator	8 uF	-	115	-	-	115	HTC-Stecker, 4-polig	
47	47	47	47	47	Kondensator	700 pF	-	116	-	-	116	Druckspule	
48	48	48	48	48	"	10000 pF	-	-	-	-	-	Kontaknehmer	Siemens St 7
49	49	49	49	49	"	500 pF	-	-	-	-	-	Grammübertrager	
50	50	50	50	50	"	700 pF	-	-	-	-	-	Kondensator	5000 pF
51	51	51	51	51	"	10000 pF	-	-	-	-	-	"	500 pF
52	52	52	52	52	"	500 pF	-	-	-	-	-	"	600 pF
53	53	53	53	53	"	700 pF	-	-	-	-	-	Widerstand	300 kOhm
54	54	54	54	54	"	50 pF	-	-	-	-	-	"	300 kOhm
55	55	55	55	55	"	100 pF	-	-	-	-	-	"	100 kOhm
56	56	56	56	56	"	200 pF	-	-	-	-	-	autom. Ein- und Ausschalter	
57	57	57	57	57	"	50 pF	-	-	-	-	-	Grammomotor	
58	58	58	58	58	"	10000 pF	-	-	-	-	-	Tonabnehmer	Thorens MD 3
59	59	59	59	59	Elektrolytkondensator	0,1 pF	-	-	-	-	-	Kondensator	700 pF
60	60	60	60	60	"	20000 pF	-	-	-	-	-	"	700 pF
61	61	61	61	61	"	15 pF	-	-	-	-	-	Widerstand	100 kOhm
62	62	62	62	62	"	16 pF	-	-	-	-	-	"	100 kOhm
63	63	63	63	63	Kondensator	0,05 pF	-	-	-	-	-	Autom. Ein- und Ausschalter	
64	64	64	64	64	Widerstand	50 kOhm	-	-	-	-	-	Grammomotor	