

| | | | |
|------|----------|------|---------|
| C.1 | 1.000 pf | R.1 | 150 Ω |
| C.2 | 75 pf | R.2 | 47 KΩ |
| C.3 | 0.025 Mf | R.3 | 1 MΩ |
| C.4 | 0.1 | R.4 | 47 Ω |
| C.5 | 200 pf | R.5 | 22 KΩ |
| C.6 | 50 | R.6 | 2.2 MΩ |
| C.7 | 75 | R.7 | 2.2 MΩ |
| C.8 | 4.000 | R.8 | 2.2 MΩ |
| C.9 | 330 | R.9 | 47 KΩ |
| C.10 | 200 | R.10 | 2.2 MΩ |
| C.11 | 200 | R.11 | 47 KΩ |
| C.12 | 200 | R.12 | 22 MΩ |
| C.13 | 200 | R.13 | 0.1 MΩ |
| C.14 | 0.05 Mf | R.14 | 0.1 MΩ |
| C.15 | 0.01 | R.15 | 0.1 MΩ |
| C.16 | 200 pf | R.16 | 180 Ω |
| C.17 | 200 | R.17 | 1000 Ω |
| C.18 | 200 | R.18 | 0.47 MΩ |
| C.19 | 5.000 | R.19 | 10 KΩ |
| C.20 | 0.025 Mf | | |
| C.21 | 0.05 | | |
| C.22 | 200 pf | | |
| C.23 | 0.01 Mf | | |
| C.24 | 3.000 | | |
| C.25 | 50+50 Mf | | |
| C.26 | 5.000 pf | | |
| C.27 | 5.000 | | |

● Solo per PH. 5558

RT. 0.25 MΩ log

5557 - 5558

RV. 0.5 MΩ log con interr.


L1-L4 Bobina aereo C2-M.
L2 > C1
L3 > filtro MF
L5-L7 > oscillat. C2-M
L6 > C1

L8 } Media Frequenza Tipo EI
L9 }


1. 2. 3. 4. 5. 6. 7. 8. 9. 10. 11. 12. 13. 14.

C.2. ● ○ ○ ○ ○ ○ ○ ○ ○ ○ ○ ○ ○ ○ ○ ○ ○
C.1. ○ ● ○ ○ ○ ○ ○ ○ ○ ○ ○ ○ ○ ○ ○ ○ ○ ○
M. ○
F. ○


V.1.




V.2.




V.3.




V.4.



V.5.



EM4.



| Valvole | Tipo | TENSIONE AI PIEDINI | | | | | | | |
|---------|-------|---------------------|-----|-----|-----|-----|-----|-----|-----|
| | | 1 | 2 | 3 | 4 | 5 | 6 | 7 | 8 |
| V.1 | ECH42 | — | 250 | 100 | — | 70 | — | 1.5 | 6.3 |
| V.2 | EF41 | — | 250 | — | — | 70 | — | — | 6.3 |
| V.3 | EBC41 | — | 100 | — | — | — | — | — | 6.3 |
| V.4 | EL41 | — | 265 | — | — | 250 | — | 7. | 6.3 |
| V.5 | AZ41 | — | 300 | — | — | — | 300 | 265 | — |
| EM4 | EM4 | 6.3 | — | 40 | 250 | — | 40 | — | — |

FIMI S. A. - PHONOLA - Mod. 5557 e 5558 Radiofonografo. Gamme d'onda: Corte 2, da 15,8 a 28 m. Corte 1, da 27,3 a 30 m. Medie da 183 a 575 m. Media frequenza 470 kc/s. Consumo rete 42 watt. Potenza indistorta 3,5 watt.