

**DESO Philadelphia 328**

Widerstände-Modell Deso PHILADELPHIA 328

		Ohm	Watt
1 Vorkreiswiderstand	R1	100 k	1/2
1 Fadingfilterwiderstand 6K7G	R2	300 k	1/2
1 Kathodewiderstand 6K7G	R3	500	1/2
1 Mischkreiswiderstand	R4	100 k	1/2
1 Kathode-Widerstand 6A8G	R5	300	1/2
1 Osc.-Gitterableitwiderstand 6A8G	R6	50 k	1/2
1 Osc.-Gitterwiderstand 6A8G	R7	300	1/2
1 Schirmgitterspann.-Tellerwiderstand	R8	10 k	1
1 do.	R9	50 k	1
1 Kathodewiderstand 6K7G	R10	300	1/2
1 NF-Diodewiderstand Nr. 1 6H6g	R11	50 k	1/2
1 do. Nr. 2 6H6g	R12	300 k	1/2
1 NF-Diodefilterwiderstand	R13	100 k	1/2
1 Lautstärkeregl. mit Schalter	R14	1 meg	
1 Kathodewiderstand 6J7G	R15	1500	1/2
1 Schirmgitterwiderstand 6J7G	R16	1 meg	1/2
1 Anodewiderstand 6J7G	R17	250 k	1/2
1 Tonblenderegler	R18	1 meg	
1 Gitterwiderstand 6A5G	R19	500 k	1/2
1 Kathodewiderstand 6A5G	R20	750 50% 3W	
1 Anodefilterwiderstand 6J7G	R21	100 k	1/2
1 Fading-Diodewiderstand	R22	10 k	1/2
1 do.	R23	250 k	1/2
1 do.	R24	2 meg	1/2
1 Magic-Eye-Widerstand	R25	2 meg	1/2
1 do.	R26	1 meg	1/2
1 Fadingfilterwiderstand	R27	1 meg	1/2
1 do.	R28	300 k	1/2
1 KW-Osc. Anodewiderstand	R29	20 k	1/2
1 Schirmgitter-Spannungsteilerwiderst.	R30	15 k	2
1 do.	R31	20 k	1
1 Anodewiderstand	R32	1 k	2
1 Anodewiderstand 6E5	R33	1 meg	1/2
1 Filterwiderstand 6A8-G	R34	5 k	1/2

Stückkondensatorenliste Deso PHILADELPHIA 328

1 Antennenkondensator		C1	200 pf
1 Trimmervorkreiskondensator	kurz	C2	3—30 pf
1 do.	mittel	C3	3—30 pf
1 do.	lang	C4	3—30 pf
1 Gitterfilterkondensator 6K7G		C5	50000 pf
1 Drehkondensator		C6 C7 C8	
1 Kathodekondensator 6K7G		C9	0,1 mf
1 Trimmer-Mischstufe	kurz	C10	3—30 pf
1 do.	mittel	C11	3—30 pf
1 do.	lang	C12	3—30 pf
1 Gitterfilterkondensator 6A8G		C13	50000 pf
1 Kathodekondensator 6A8G		C14	0,1 mf
1 Osc.-Gitterkondensator 6A8G		C15	100 pf
1 Trimmer-Osc.	kurz	C16	3—30 pf
1 Osc.-Padding-Kondensator	kurz	C17	5000 pf
1 Trimmer-Osc.	mittel	C18	3—30 pf
1 Osc. Padding	mittel	C19	428 pf
1 Trimmer Osc.	lang	C20	3—30 pf
1 Osc.-Padding	lang	C21	180 pf
1 Schutzgitterkondensator 6A8G		C22	0,1 mf
1 BF-Kondensator, Anode 6A8G		C23	100 pf
1 BF-Kondensator, Gitter 6K7G		C24	100 pf
1 Kathodekondensator 6K7G		C25	0,1 mf
1 Fading-Diodekondensator 6H6G		C26	100 pf
1 BF-Kondensator, Anode 6K7G		C27	100 pf
1 BF-Kondensator, Diode 6H6G		C28	100 pf
1 NF-Diodekondensator 6H6G		C29	100 pf
1 NF-Diodefilterkondensator 6H6G		C30	100 pf
1 NF-Koppl.-Kondensator		C31	50000 pf
1 Kathodekondensator 6J7G		C32	20 mf
1 Anode-HF-Filterkondensator 6J7G		C33	100 pf
1 Tonblendekondensator		C34	1000 pf
1 Gitterkoppl.-Kondensator 6A5G		C35	50000 pf
1 Kathodekondensator 6A5G		C36	20 mf
1 Anodefilterkondensator 6J7G		C37	0,5 mf
1 Schirmgitterkondensator 6J7G		C38	0,1 mf
1 Regelfilterkondensator		C39	50000 pf
1 Fadingfilterkondensator		C40	50000 pf
1 Schirmgitterfilterkondensator 6K7G		C41	0,1 mf
1 KW-Anodekondensator		C42	50000 pf
1 Netzfilterkondensator		C43	48 mf
1 Netzfilterkondensator		C44	16 mf
1 Parallelfilterkondensator C44		C45	0,1 mf
1 NF-Sperrkreiskondensator		C46	ca. 3000 pf
1 Störschutzkondensator		C47	5000 pf
1 Störschutzkondensator		C48	5000 pf
1 Filterkondensator 6A8G		C49	50000 pf