



Wellenbereichumschalter in Stellung KW.
Tonabnehmerschalter in Stellung Rundfunk.

64 A

Mediator

Bobines

Résistances

Condensateurs

S 1	50	ohms
S 2	400	"
S 3	1	"
S 4	1	"
S 5	390	"
S 6	3,5	"
S 7	1	"
S 8	28	"
S 9	5	"
S 10	115	"
S 11	45	"
C 6	3-30	uuF
C 7	3-30	"
C 8	3-30	"
S 12	2,5	ohms
S 13	1	"
S 14	280	"
S 15	4,5	"
S 16	470	"
S 17	45	"
C 9	3-30	uuF
C 10	3-30	"
C 11	3-30	"
S 18	1	"
S 19	1	"
S 20	8,5	"
S 21	3,5	"
S 22	20	"
S 23	3,5	"
C 12	3-30	uuF
C 13	3-30	"
C 14	3-30	"
S 24	7,5	ohms
S 26	7,5	"
C 29	91	uuF
	103	uuF
C 30	97	"
	109	"
S 27	3,5	ohms
S 28	4,5	"
S 29		
S 30	5	"
C 33	103	uuF
	117	"
C 34	103	"
	117	"
S 31	640	ohms
S 32	1	"
S 40	280	"
S 41	280	"

R 1	0,8	Mg
R 2	400	ohms
R 6	32	"
R 7	0,8	Mg
R 8	50000	ohms
R 9	32000	"
R 10	8000	"
R 11	500	"
R 12	50000	"
R 13	1,25	Mg
R 14	20000	ohms
R 15	160	"
R 17	320	"
R 18	50000	"
R 20	0,5	Mg
R 21	50000	ohms
R 22	0,65	"
R 64	50000	"
R 24	5	Mg
R 25	0,64	"
R 26	2	"
R 27	0,64	"
R 28	1	"
R 29	1000	ohms
R 30	160	"
R 31	200	"
R 32	100	"
R 33	50000	"
R 34	50	"
R 35	2000	"
R 37	2000	"
R 60	1600	"
R 61	8000	"
R 62	10000	"
R 63	0,8	Mg
R 64	50000	ohms

C 1	28	uF
C 2	32	uF
C 3	11-490	uuF
C 4	11-490	uuF
C 5	11-490	uuF
C 6-C 14	3-30	uuF
C 15	200	uuF
C 16	200	uuF
C 17	80	uuF
C 18	100	uuF
C 19	0,1	uuF
C 21	100	uuF
C 22	0,1	uF
C 23	0,1	uF
C 24	32	uF
C 25	50	uuF
C 26	4000	uuF
C 27	400	uuF
C 28	0,1	uF
C 29	103	uuF
C 30	109	uuF
C 31	50000	uuF
C 32	50000	uuF
C 33	117	uuF
C 34	117	uuF
C 35	8	uuF
C 36	50	uuF
C 37	50000	uuF
C 41	3,200	uuF
C 42	50000	uuF
C 43	2	uuF
C 44	64	uuF
C 45	250	uuF
C 46	25	uF
C 47	2000	uuF
C 48	40	uuF
C 49	50000	uuF
C 50	50000	uuF
C 62	20000	uuF
C 70	64000	uuF
C 71	2000	uuF
C 72	125	uuF