



PYE 1373

COMMUNICATIONS

Transistor Table

Transistor	Emitter (V)	Base (V)	Collector (V)
TR1	BF195	5.6	4.9
TR2	BF194	6.5	5.5
TR3	BF194	5.1	4.3
TR4	BC108	5.4	4.4
TR5	AC128	0.03	0.15
TR6	AC128	0.03	0.15
TR7	BC108	6.2	5.1

Quiescent current 18mA.

Resistors

R1	6.8kΩ	A1
R2	18kΩ	A1
R3	2.2kΩ	A1
R4	180Ω	A1
R5	560Ω	A1
R6	82kΩ	A2
R7	12kΩ	A2
R8	820Ω	A1
R9	270Ω	A1
R10	2.2kΩ	A2
R11	6.8kΩ	B1
R12	12kΩ	A2
R13	1kΩ	B1
R14	100Ω	B2
R15	39Ω	B1
R16	470Ω	B1
R17	18kΩ	B2
R18	18kΩ	B1
R19	1kΩ	B2
R20	39kΩ	B1
R21	1kΩ	B1
R22	470Ω	B1
R23	2.7kΩ	B1
R24	VA1040	B1
R25	100Ω	B1
R26‡	1MΩ	B1
R27	2.2Ω	B1
R28	100Ω	B1
R29	10kΩ	B1
R30	18kΩ	B1
R31	47kΩ	B2

Capacitors

R32	82kΩ	B1
RV1	20kΩ	A1
RV2	10kΩ	A1
C1	39pF	B2
C2	15pF	A2
C3	20pF	A2
C4	20pF	B1
C5	180pF	B1
C6	215pF	A1
C7	0.02μF	A1
C8	208pF	A2
C9	20pF	A2
C10	0.25μF	A1
C11	0.01μF	A1
C12	0.01μF	A1
C13	360pF	A1
C14	0.04μF	A1
C15	6.4μF	A1
C16	0.1μF	A1
C17	0.04μF	B1
C18	360pF	A2
C19	0.04μF	A2
C20	0.04μF	A2
C21	0.1μF	A1
C22	0.04μF	B2
C23	360pF	B1
C24	0.01μF	B1
C25	0.01μF	B1
C26	4μF	B1
C27	2.5μF	B2
C28	0.01μF	A1

C29	0.04μF	B1
C30	200μF	B2
C31	2000pF	B1
C32	64μF	B2
C33	0.1μF	B1
C34	200μF	B1
C35	0.01μF	B1
C36	0.02μF	B2
C37	0.01μF	B2
C38	0.02μF	B2

Coils and Transformers

L1	—	B2
L2	—	B2
L3	—	A2
L4	—	A1
L5	—	A2
L6	—	B2
L7	3Ω	A1
T1	—	A1
T2	—	A1
T3	—	B2
T4	—	B1
T5	—	B1

Miscellaneous

S1-S7	—	A1
S8	—	A2
D1	AA119	A2
D2	AA119	B1

‡ Omitted from later models.

C	37	36	35	1,2	3	7	10,11,12,8,6,9	4	5	13,14	15	16,17,18,19	21,20,22,23	24	25	26	29,28,30,27,38	31,32	33	34	C						
R	31,32	29,30				1,2	3,4				5	6	7	8	9	10	11,12	13,14	15	16	17	RV2, RV1	19,18,20	21	22,24,23,25	26,27,28	R

