- ▲ 12-BAND RECEIVER LW/MW/FM STEREO/SW (1-9)
- EASY ANALOG TUNING
- LED TUNING INDICATOR
- FM STEREO HEADPHONE JACK
- COMPACT SIZE
- DC-IN JACK
- POWERED BY TWO "AA" BATTERIES
- STEP-UP FEATURE NEW FEATURE





features

▲ 12-BAND RECEIVER – LW/MW/FM STEREO/SW (1-9) lets you listen to a worldwide range of frequencies at home and abroad, including FM stereo, MW, LW, and Shortwave bands 1-9

- EASY ANALOG TUNING simplifies tuning-in desired stations
- LED TUNING INDICATOR provides accurate indication of center frequency
- FM STEREO HEADPHONE JACK allows for FM stereo reception as well as private listening and improved sound clarity in noisy environments
- **COMPACT SIZE** means you can you slip this lightweight radio into a jacket pocket or briefcase for easy portability
- DC-IN JACK lets you use an optional AC Adaptor to operate the radio
- **POWERED BY TWO "AA" BATTERIES** for on the go listening anywhere in the world

specifications

FREQUENCY RANGE: FM: 87.6-108MHz AM (MW): 530-1602kHz SW1: 4750-5060kHz SW2: 5900-6200kHz SW3: 7100-7350kHz SW4: 9400-9990kHz SW5: 11600-12100kHz SW6: 13570-13870kHz SW7: 15100-15800kHz SW8.17480-17900kHz SW9: 21450-21750kHz LW: 153-279kHz INPUT: DC in, 3V **OUTPUT:** headphone jack **ANTENNA SYSTEM:** FM/SW: Telescoping antenna MW/LW: Built-in ferrite bar antenna SPEAKER: 2 1/4" (57mm) **POWER REQUIREMENTS:** "AA" x 2 batteries (not incl.) BATTERY LIFE: Approx. 30 hours **COLOR:** Black **DIMENSIONS (WHD):** 6 ³/8" x 3 ⁵/8" x 1 ³/8" (162 x 93.8 x 33.3mm) WEIGHT: 12 oz (340g) with batteries SUPPLIED ACCESSORIES: Short Wave Guide Book OPTIONAL ACCESSORIES: AC Power Adaptor, Car Power Adaptor DCC-E130L

©2002 Sony Electronics Inc.

Reproduction in whole or in part without written permission is prohibited. All rights reserved. Sony and World Band Receiver are trademarks of Sony.

Features and specifications are subject to change without notice. Non-metric weights and measures are approximate.