


6D6

PENTHODE
(HF - MF)

6D6

V_f	=		6,3	V.
I_f	=		0,3	A.
V_a	=	100	250(max)	V.
V_{g2}	=	100	100(max)	V.
$V_{g1}(\text{min})$	=	—3	—3	V.
I_a	=	8	8,2	mA.
I_{g2}	=	2,2	2,0	mA.
g	=	375	1.280	
R_i	=	0,25	0,8	M. Ω
$S(\text{max})$	=	1.500	1.600	mA/V.
C_i	=		4,7	$\mu\mu\text{F.}$
C_o	=		6,5	$\mu\mu\text{F.}$
R_k	=	400	400	Ω



6D6