

6G6G**6G6G**

PENTHODE
(E_A)

V _f	=	6,3	V.
I _f	=	0,15	A.
V _a	=	180	V.
V _{g2}	=	180	V.
V _{g1}	=	-9	V.
I _a	=	15	mA.
R _i	=	0,175	M.Ω
S	=	2,3	mA/V.
g	=	400	
R _a	=	10.000	Ω
R _k	=	510	Ω
W _o	=	1,1	W _{tt.}
d% (tot)	=	10	%

