

PENTHODE (E)

V_f	=			6,3	V.
I_f	=			0,3	A.
V_a	=	100	135	180	250(max) V.
V_{g2}	=	100	135	180	250(max) V.
V_g	=	-9	-13,5	-18	-25 V.
I_a	=	7	9	14	22 mA.
I_{g2}	=	1,2	1,5	2,4	3,8 mA.
g	=	120	120	120	120
R_i	=	0,14	0,13	0,115	0,1 M.Ω
S	=	0,875	0,925	1,05	1,2 mA/V.
$W_o(10\%)$	=	0,27	0,55	1,0	2,5 Wtt.
R_a	=	15	13,5	11,6	10 kΩ
R_k	=	1,1	1,1	1,1	0,97 kΩ

