



TERMINALS	A.C. VOLTS	SECONDARY
1		Center Tap for 280 Plate
2	2.67	Center Tap for 245 Tubes
3-4	2.68	Heaters of 224 and 227 Tubes
5-6	5.00	Filaments of 245 Tubes
8-9	7.50	Filament of 280 Tube
7-10		Plate of 280 Tube
Red Wire		Center Tap for 224 and 227 Tubes
Red Wire		Primary
Red Wire		Primary } Through panel together

**Model 76.**

Vol. Contr. set to max. - Line Volts: 115						
Tube	Location	Fil.	Plate	S.G.	Contr.	Cathode Plate
Type	Volts	Volts	Volts	Gr.	Volts	Ma.
#24	1 R.F.	2.3	145	90	3.	13.
#24	2 R.F.	2.3	145	90	3.	13.
#24	Det.	2.3	36	30	1.4	12.
#27	1 A.F.	2.3	140		1.	10.
#45	2 A.F.	2.2	230		46.	30
#45	2 A.F.	2.2	230		46.	30
#80	Rect.	4.5				50