

DIAG Nº	PART Nº	DESCRIPTION	
C1	22-927	TWO GANG VARIABLE	
C2	22-829	.05 MFD	200V
C3	22-828	.05 MFD	400V
C4	22-716	.0005 MFD	600V
C5	22-127	.25 MMFD	600V
C6	22-825	.1 MFD	400V
C7	22-182	.00025 MFD	600V
C8	22-327	.02 MFD	200V
C9	22-830	.02 MFD	600V
C10	22-827	.1 MFD	200V
C11	22-854	.0005 MFD	600V
C12	22-219	.03 MFD	200V
C13	22-627	.002 MFD	1000V
C14	22-448	.001 MFD	600V
C15	22-229	.005 MFD	600V
C16	22-470	.00015 MFD	600V
C17	22-954	.00035 MFD	600V
C18	22-492	.002 MFD	600V
C19	22-868	COMPENSATING COND	
C21	22-930	DUAL OSC PADDER	
C22	22-933	.6 MFD ELECTROLYTIC	450V
C23		.1 MFD	450V
C24	22-719	.1 MFD	350V
C25	22-358	.002 MFD	600V
C26	22-525	.005 MFD	1000V
C27	22-162	.0001 MFD	600V
R1	63-589	1.0 M OHM	½ W
R2	63-1077	1.8 M OHM	1 W
R3	63-587	4700 OHM	½ W
R4	63-595	100 M OHM	½ W
R5	63-593	.47 M OHM	½ W
R6	63-643	1.8 M OHM	½ W
R7	63-605	1000 OHM	½ W
R8	63-271	1 MEGOHM	½ W
R9	63-774	.220 M OHM	½ W
R10	63-711	.22 M OHM	½ W
R11	63-296	.220 M OHM	½ W
R12	63-597	.470 M OHM	½ W
R13	63-1075	VOLUME CONTROL	
R14	63-594	.68 M OHM	½ W
R15	63-677	.33 M OHM	1 W
R16	63-796	1.0 M OHM	½ W
R17	63-576	68 OHM	½ W
R18	63-998	3 SECTION CANDOHM	
R19	63-151	1.5 M OHM	1 W
R20	63-574	33 OHM	½ W
1		WAVEMAGNET ASSEMBLY	
2	S 7504	ANTENNA COIL ASSEMBLY	
3	S 7691	OSCILLATOR COIL ASSEMBLY	
4	S 7507	OSC COUPLER COIL ASSEM	
5	S 7649	AUTOMATIC TUNING UNIT -	
6	85-280	BAND SELECTOR SWITCH	
7	S 7559	WAVE TRAP COIL ASSEMBLY	
8	85-171	WAVEMAGNET SWITCH	
9	85-171	TELEVISION SWITCH	
10	95-625	1ST I F TRANS	
11	95-663	2ND I F TRANS	
12	S 7643	TONE CONTROL SW ASSEM	
13	95-627	POWER TRANS 60~/115V	
14	100-36	PILOT LIGHT 6.3 V. .25A	
15	S 7526	R F CHOKE	
16	S 8142	LOOP LOADING COIL ASSEM (NOTE USED ON SOME MODELS)	
A		1ST I.F. TRANS. PRI	
B		1ST I.F. " SEC	
C		2ND I.F. " PRI	
D		2ND I.F. " SEC	
E		WAVE TRAP	
F		BROADCAST OSC (SEE NOTE)	
G		ANTENNA BROADCAST	
K		SHORT WAVE OSC (SEE NOTE)	
M	22-988	SHORT WAVE DET	
N		POLICE BAND OSC (SEE NOTE)	
Q	22-988	POLICE BAND DET	
J	22-463	BROADCAST PADDER	

NOTE: TRIMMERS F K & N ARE MOUNTED ON STRIP # 22-850

Models 8S443—8S451—8S463

Chassis No. 5808

I.F. FREQUENCY 455 KC
8 TUBE SUPERHETERODYNE
CHASSIS Nº 5808 3 BAND
ZENITH RADIO CORPORATION