

<u>DWG.</u> <u>Nº</u>	<u>PART</u> <u>Nº</u>	<u>DESCRIPTION</u>
--------------------------	--------------------------	--------------------

N ^o	N ^o	DESCRIPTION
C1	22-300	365 MFD 200V
C2	22-250	.05 MFD 200V
C3	22-157	25 MFD 600V
C4	22-199	.5 MFD 200V
C5	22-162	25 MFD 600V
C6	22-183	01 MFD 200V
C7	22-188	.02 - 400V
C8	22-02	.001 - 600V
C9	22-170	1 - 400V
C10	22-207	.03 - 600V
C12	22-305	2.5 MFD 250V
C13	22-292	300-000 MFD
C14	22-125	0.01 - 400V
C15	22-304	0036 MFD 60V

R1	63-280	49M	1W
R2	63-377	170	1W
R3	63-255	490M	1W
R4	63-238	990M	1W
R5	63-353	10M	2W
R6	63-373	11M	2W
R7	63-366	200M	POL. CONTROL
R8	63-351	17035	POL. CONTROL
R9	63-316	50M	POL. CONTROL
R10	63-278	99M	1W
1	5-3397	SELECTOR DET COIL	
2	85-62	SHORT WAVE SWITCH	
3	5-3129	OSC COIL ASSEM	
4	95-244	HTLF TRANS	
5	95-245	2N61F	
6	49-79	8.5 SPEAKER - 1000	5000 FIE
7	49-55	10 SPEAKER - 1000	5000 FIE
8	95-234	POWER TRANS	50-600 OHM
9	95-229		25 CYCLES
10	5-3377	16 METER DET COIL ASSEM	

5	32-45	8" SPEAKER - 1000~ FIELD (MO. 945)
6	49-79	10" SPEAKER - 1000~ (MO. 950)
7	49-85	POWER TRANS 25 CYCLE
8	95-234	16 METER DET. COIL ASSEMBLY
9	95-229	
10	5-317	

1st DET.
056
6-4-7

1.F.
6-D-6

POWER
42

THREE BANDS

535 KG - 1520 KG.
1460 KG - 4550 KG.
5800 KG - 18,500 KG.

I.F. FREQUENCY 252.5 K.C.
5 TUBE SUPERHETERODYNE
CHASSIS NOS. 5508 & 5509

MODEL'S 945-950

ZENITH RADIO CORP.
CHICAGO, ILL.

