



PHILIPS SERVICE 690 A

ZF = 452 kHz

BOBINES - SPULEN

S1	50 Ohm	S18	<1 Ohm	S34	7 Ohm
S2	300 Ohm	S19	<180 Ohm	S35	5 Ohm
S3	<1 Ohm	S20	<1 Ohm	S36	20 Ohm
S4	<1 Ohm	S20a	6, 5 Ohm	S37	7, 5 Ohm
S5	<1 Ohm	S21	<1 Ohm	S38	4 Ohm
S6	<1 Ohm	S22	<1 Ohm	S41	2, 6 Ohm
S7	<1 Ohm	S23	<1 Ohm	S42	4, 2 Ohm
S8	<1 Ohm	S24	<1 Ohm	S43	2, 6 Ohm
S9	<1 Ohm	S25	<1 Ohm	S44	4, 2 Ohm
S10	<1 Ohm	S26	<1 Ohm	S45	3200 Ohm
S11	<1 Ohm	S27	<1 Ohm	S46	3200 Ohm
S12	<1 Ohm	S28	<1 Ohm	S48	<1 Ohm
S13	<1 Ohm	S29	<1 Ohm	S50	<1 Ohm
S14	<1 Ohm	S30	<1 Ohm	S52	43 Ohm
S15	<1 Ohm	S31	<1 Ohm	S54	<1 Ohm
S16	<1 Ohm	S32	<1 Ohm	S55	<1 Ohm
S17	100 Ohm	S33	3 Ohm	S56	<1 Ohm
				S57	<1 Ohm

CONDENSATEURS - KONDENSATOREN

C1	50 uF	C17	82 pF	C33	18 pF
C2	50 uF	C18	400-575 pF	C34	1, 8 pF
C3	100 uF	C19	30 pF	C35	8200 pF
C4	12-492 pF	C20	30 pF	C36	8200 pF
C5	12-492 pF	C21	175 pF	C37	330 pF
C6	15 pF	C22	22 pF	C38	47 pF
C7	30 pF	C23	12 pF	C39	0, 1 pF
C8	30 pF	C24	30 pF	C40	10000 pF
C9	82 pF	C25	115 pF	C42	22000 pF
C10	220 pF	C26	115 pF	C44	10 pF
C11	30 pF	C27	115 pF	C45	100 pF
C12	12 pF	C28	68000 pF	C48	47000 pF
C13	56 pF	C29	115 pF	C50	47000 pF
C14	470 pF	C30	115 pF	C51	47000 pF
C15	47000 pF	C31	18 pF	C52	30 pF
C16	47000 pF	C32	820 pF	C53	100 pF
				C60	390 pF

RESISTANCES - WIDERSTAENDE

R1	1200 Ohm	R13	47000 Ohm	R25	0, 68 Meg
R2	68 Ohm	R14	0, 65 Meg	R27	0, 68 Meg
R3	33 Ohm	R15	2 Meg	R28	0, 82 Meg
R4	0, 82 Meg	R16	0, 22 Meg	R30	1000 Ohm
R5	47000 Ohm	R17	2 Meg	R35	2, 2 Meg
R6	22000 Ohm	R18	0, 2 Meg	R36	1 Meg
R7	24800 Ohm	R19	0, 82 Meg	R37	1 Meg
R8	82000 Ohm	R20	0, 22 Meg	R40	3, 3 Meg
R9	0, 68 Meg	R21	1, 5 Meg	R47	47000 Ohm
R10	56000 Ohm	R22	0, 1 Meg	R48	1000 Ohm
R11	0, 15 Meg	R23	1, 5 Meg	R49	10000 Ohm
R12	0, 82 Meg	R24	0, 15 Meg	R50	150 Ohm