





UNDA RADIO — Modello Super Quadri Unda 639. — Produzione 1938-39. — Gamme: cc. (15-30), c. (30-80), m. (206,5-600), l (870-1870) — Potenza d'uscita: 6,5 W — Media frequenza: 450 kHz

Valvola	Catodo	Schermo	Placca	Filamento
6 I 7-G	6	150	250	6,1
6 C 5-G	6	—	150	6,1
6 K 7-G	5,2	95	240	6,1
6 Q 7-G	1,8	—	120	6,1
6 I 6-G	13	255	245	6,1
80	—	—	—	360

Corrente anodica totale: ca. 120 m A.